



GENMAC Combipro G7900HC-M5 GENERATOR 8,0KVA

Reference:

GENMAC COMBIPRO G7900HC-M5 THREE-PHASE GENERATOR 8,0KVA

The generator Genmac Combipro G7900HC-M5 Single/ Three phase is equipped with a Honda gasoline powered engine capable of delivering a power of 8,0KVA with capacitor voltage regulator (AVR optional).

The Generators of the **Genmac Combipro G7900 series** are among the most **silent** in their category, thanks to the side closing panels and the oversized muffler.

The front panel of the Genmac 8,0KVA generator is protected by a canopy and is complete with a back panel that guarantees protection and insulation from water. The generator is equipped with electric starter and injection engine with electronic speed regulation.

The Genmac G7900 8,0KVA generators are equipped with a **25-liter tank** with a large cap that is convenient to unscrew even with work gloves, filter and **fuel level indicator**. There is also a manual fuel circuit shut-off tap to prevent fuel leakage.

The Genmac Combipro mounts a **Honda OHV 4-stroke petrol engine**. They are very reliable engines that guarantee efficient combustion and **low fuel consumption**. The engines with 8,0KVA generators are also equipped with a protection system that causes the **engine to stop if the oil level is too low**.

The 8,0KVA generator with capacitor voltage regulator, on request it can be supplied with AVR.

AVR Voltage Regulator

All models in the Genmac Combipro series are available with optional AVR regulator. The AVR is a device that allows to **maintain the output more constant and less load-dependent**. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

The model equipped with AVR card is highly recommended, as it guarantees a significant improvement in the stability of the output voltage; this feature makes the generators particularly suitable with common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you can enjoy greater stability and thus increase the life of your devices.

TECHNICAL FEATURES OF GENERATOR GENMAC COMBIPRO G7900HC-M5

Voltage regulator : capacitor (AVR Optional)
Power supply: Gasoline
Starting: Manual
Phase type: Singlephase / Threephase
Singlephase continuous output: 2.4KVA / 2.2KW
Maximum singlephase output: 2. 6KVA / 2.4KW

Threephase continuous output: 7.3KVA / 5.8KW
 Threephase maximum output: 8,0KVA / 6.4KW
 Motor: Honda GX390
 Socket panel: 1 x schuko 230V - 1 x 16A 230V - 1 x 16A 400 V
 Emission standard: Stage V
 Voltage: 230 / 400V
 Frequency: 50 Hz
 3000 rpm
 Tank: 25 Lt.
 Autonomy @ 75%: 12 h fixed rpm
 Boosting: Manual
 Length (mm): 800
 Width (mm): 640
 Height (mm): 700
 Dry weight (Kg): 106

If you are looking for another product then you can see on [our catalog](#) other Generator

Images and technical data not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	2.4
Continuous power single phase (KW)	
Maximum power single phase (KVA)	2.6
Continuous power single phase (KVA)	
Maximum power three phase (KW)	6.4
Continuous power three phase (KW)	5.8
Maximum power three phase (KVA)	8
Continuous power three phase (KVA)	7.3
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Cooling	Air
Poles	2
Fuel tank capacity (L)	25
Running time (h)	12

Acoustic pressure	69 dB(A) at 7 m
-------------------	-----------------

Length (mm)	
-------------	--

Width (mm)	
------------	--

Height (mm)	700
-------------	-----

Dry weight (Kg)	106
-----------------	-----

Silenced	Yes
----------	-----

Super silenced	No
----------------	----

ATS Switch device	No ATS
-------------------	--------

Voltage regulator	AVR (optional)
-------------------	----------------

Engine manufacturer	Honda
---------------------	-------
