



## PRAMAC ES4000 Single-phase 3.1 KW AVR generator set

Reference: PE292SH100A

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated.

Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

- ? Air cooling
- ? Oil Guard protection
- ? Tear-off starter
- ? Synchronous alternators available with AVR
- ? Sturdy structure with tubular supporting frame
- ? Sockets on headphones with thermal protection.
- ? Oversized tanks (11 litres)
- ? Side protection strips

The image is purely indicative.

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.1
Continuous power single phase (KW)	2.6
Maximum power single phase (KVA)	3.4
Continuous power single phase (KVA)	2.9
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A IP54 SCHUKO
Engine	Honda GX200, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical

Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm <sup>3</sup> )	196
Oil capacity (L)	0.6
Cooling	Air
Alternator	With brushes
Poles	2
Fuel tank capacity (L)	11
Consumption (L/h)	1.2 at 75% of the load / 1.6 at 100% of the load
Running time (h)	9.3 at 75% of the load / 7 at 100% of the load
Acoustic power	95 dB(A)
Acoustic pressure	67 dB(A) at 7 m
Length (mm)	623
Width (mm)	409
Height (mm)	500
Dry weight (Kg)	43
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda