



## PRAMAC ES5000 SINGLE-PHASE PETROL genset, AVR

Reference: PE402SH100D

Gasoline model developed by Pramac to guarantee a high level of quality and performance at an attractive price. Generator ideal for intense applications, characterized by a sturdy structure with tubular supporting frame that simplifies both its use and maintenance operations. The essential tool to satisfy professional applications.

HONDA GX series petrol engines  
Air cooling  
Oil Guard protection  
Tear-off starter  
Synchronous alternators available with AVR  
? Sturdy structure with tubular supporting frame  
Sockets on headphones with thermal protection.  
? Oversized tanks (11 litres)  
? Side protection strips

The image is purely indicative.

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	4.6
Continuous power single phase (KW)	3.9
Maximum power single phase (KVA)	5.1
Continuous power single phase (KVA)	4.2
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	Honda GX270 Recoil, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical

Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm <sup>3</sup> )	270
Oil capacity (L)	1.1
Cooling	Air
Alternator	With brushes
Poles	2
Fuel tank capacity (L)	11
Consumption (L/h)	1.6 at 75% of the load / 2.2 at 100% of the load
Running time (h)	6.6 at 75% of the load / 5 at 100% of the load
Acoustic power	97 dB(A)
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	729
Width (mm)	500
Height (mm)	536
Dry weight (Kg)	61
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda