



PRAMAC S6000 Single/three-phase Generator set 5.5KW

Reference: PD572TY4001

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	2.56
Continuous power single phase (KW)	2.4
Maximum power single phase (KVA)	3.2
Continuous power single phase (KVA)	3
Maximum power three phase (KW)	5.5
Continuous power three phase (KW)	4.5
Maximum power three phase (KVA)	6.9
Continuous power three phase (KVA)	5.6
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	
Engine	Yanmar L100N Electric, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Elettrico

Engine capacity (cm ³)	435
Oil capacity (L)	1.6
Cooling	Air
Alternator	Brushless
Poles	2
Fuel tank capacity (L)	24
Consumption (L/h)	1.45 at 75% of the load / 1.94 at 100% of the load
Running time (h)	16.55 at 75% of the load / 12.37 at 100% of the load
Length (mm)	840
Width (mm)	641
Height (mm)	696
Dry weight (Kg)	124
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	Compound
Engine manufacturer	Yanmar