



PRAMAC S8000 SINGLE PHASE AVR

Reference: PD612SH2Z02

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

Technical Sheet

| | |
|-------------------------------------|---|
| Phase | Single phase |
| Maximum power single phase (KW) | 6.4 |
| Continuous power single phase (KW) | 5.5 |
| Maximum power single phase (KVA) | 7.2 |
| Continuous power single phase (KVA) | 6 |
| Fuel | Gasoline |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 |
| Sockets configuration | |
| Engine | Honda GX390 Electric, naturally aspirated |
| Engine rpm (rpm) | 3000 |
| Speed governor | Mechanical |
| Starting system | Elettrico |
| Engine capacity (cm ³) | 389 |
| Oil capacity (L) | 1.1 |
| Cooling | Air |
| Alternator | With brushes |

| | |
|------------------------|---|
| Poles | 2 |
| Fuel tank capacity (L) | 26.5 |
| Consumption (L/h) | 2.15 at 75% of the load / 2.87 at 100% of the load |
| Running time (h) | 12.27 at 75% of the load / 9.23 at 100% of the load |
| Acoustic power | 97 dB(A) |
| Acoustic pressure | 73 dB(A) at 7 m |
| Length (mm) | 840 |
| Width (mm) | |
| Height (mm) | 753 |
| Dry weight (Kg) | 109 |
| Silenced | No |
| Super silenced | No |
| Product type | Generator |
| ATS Switch device | Optional ATS |
| Voltage regulator | AVR |
| Engine manufacturer | Honda |