



## GENSET MG 12 I-H/AE - SINGLE-PHASE/THREE-PHASE GENERATOR 11 KVA AVR

Reference: MG 12 I-H/AE

### GENSET MG 12 I-H/AE

The GENSET MG 12 I-H/AE is a single-phase/three-phase 11 KVA petrol generator with electric start and AVR voltage regulator. This generator is also available in the version with automatic panel and remote control. The GENSET MG 12 I-H/AE also has a low fuel consumption: only 5.5 Lt/h at 75% of the load. The GENSET MG 12 I-H/AE generator set, thanks to the high quality and efficiency of its components, is ideal for various types of work: from small hobby jobs to large construction sites.

Images and technical data are not binding.

### Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	3.2
Maximum power single phase (KVA)	4
Maximum power three phase (KW)	8.8
Continuous power three phase (KW)	8
Maximum power three phase (KVA)	11
Continuous power three phase (KVA)	10
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A CEE - 1 x 230V 16A CEE
Engine	Honda GX630, 4 stroke, OHV
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	688

Number cylinders	2
Cooling	Air
Alternator	Synchronous
Protection degree	IP23
Motor insulation class	H
Fuel tank capacity (L)	29
Consumption (L/h)	5.5
Running time (h)	5.27
Acoustic power	98 dB(A)
Acoustic pressure	73 dB(A) at 7 m
Length (mm)	904
Width (mm)	507
Height (mm)	823
Dry weight (Kg)	148
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda