



## LINZ E1X13M F/4 Three-phase alternator 4 poles 16 kVA 50 Hz AVR

Reference: E1X13M F/4 50 Hz

E1X13/4 series are three-phase brushless alternators 4 poles with exciter and electronic regulation (AVR).

### CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION

### Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	12.8
Continuous power three phase (KVA)	16
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	1500
Alternator	Synchronous
Poles	4
Three-phase power (KVA)	16
Protection degree	IP21

---

Motor insulation class	H
Length (mm)	544
Width (mm)	260
Height (mm)	373
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	96

---