



CGM C3500

Reference: CGM C3500

CGM C3500 Singlephase Generator 3,5 KVA

Generator CGM C3500 singlephase 3.5 KVA with Honda engine powered by gasoline STAGE V at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers.

The CGM C3500 Generator is composed by a Made in Italy alternator of Linz or NSM, self-excited without brushes and with voltage regulator **AVR**.

The CGM C3500 generator is equipped with manual recoil start and low fuel consumption, in fact it consumes only 1.1 liters/hour at 75% load for a range of almost 3 hours.

This C3500 generator is perfect for outdoor use such as hobby use.

The CGM C3500 generator is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, rigs, campgrounds, hobbies, construction sites etc. The C3500 3000 RPM generator is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical features of CGM C3500 generator:

Phase type: Single phase
Maximum power: 3.4 KW
Continuous power: 3.1 KW
Maximum power: 3.8 KVA
Continuous power: 3.5 KVA
Fuel: Gasoline
Voltage: 230 V
Frequency: 50 Hz
Motor: HONDA GX200
Emission standard: Stage V
Engine RPM: 3000 rpm
Start: Manual
Voltage regulator system: AVR
Consumption: 1.1 Lt/h at 75% load
Tank capacity: 3.1 Lt
Autonomy: 2.8 h at 75% load
Length: 625 mm
Width: 390 mm
Height: 435 mm
Weight: 38 Kg

Discover the full range reserved for [current generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding and may be subject to revisions by the manufacturer

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.4
Continuous power single phase (KW)	3.1
Maximum power single phase (KVA)	3.8
Continuous power single phase (KVA)	3.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A 3P CEE - 1 x 230V SCHUKO
Engine	HONDA GX200
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm ³)	196
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	3.1
Consumption (L/h)	1.1
Running time (h)	2.8
Length (mm)	625
Width (mm)	390
Height (mm)	435
Dry weight (Kg)	38
Silenced	No
Super silenced	No

Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda
