



## CGM C7000E SINGLE PHASE GENERATOR 7KVA

Reference: CGM C7000E

### CGM C7000E single-phase generating set 7 KVA

Generator CGM C7000E single-phase 7 KVA set with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C7000E generator set is composed of a Made in Italy alternator from Linz or NSM, self-excited without brushes and with AVR voltage regulator. The CGM C7000E generator set is equipped with electric start with 12 V battery or manual recoil starter with recoil starter and with a low fuel consumption, in fact it consumes only 2 liters/hour at 75% of the load.

This generator is perfect for outdoor use as for example for hobby use. The CGM C7000E generating set is part of the CLASSIC series and is easily adaptable to various uses such as homes, mobile facilities, camping, hobbies, construction sites etc..

The C7000E generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

#### Technical specifications of CGM C7000E generator set:

Phase type: Single phase  
Maximum single phase power: 6.9 KW  
Maximum single phase continuous use power: 6.3 KW  
Maximum single phase power: 7.7 KVA  
Single-phase continuous use power: 7.7 KVA  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Engine: HONDA GX390  
Engine RPM: 3000 RPM  
Start: Electric  
Voltage regulator system: AVR  
Consumption: 2 Lt/h at 75% load  
Tank capacity: 6.1 Lt  
Autonomy: 3 h at 75% load  
Length: 780 mm  
Width: 510 mm  
Height: 500 mm  
Weight: 82 Kg

Discover the full range reserved for [Ground generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.9
Continuous power single phase (KW)	6.3
Maximum power single phase (KVA)	7.7
Continuous power single phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	389
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	6.1
Consumption (L/h)	2
Running time (h)	3
Length (mm)	780
Width (mm)	510
Height (mm)	500
Dry weight (Kg)	82
Silenced	No
Super silenced	No
Product type	Generator

---

ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda

---