



CGM C13000HE

Reference: CGM C13000HE

CGM C13000HE Single-phase Generator 12 KVA

Generator CGM C13000HE single-phase 12 KVA with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C13000HE generator is composed of a Made in Italy Linz or NSM alternator, self-excited without brushes and with voltage regulator or AVR.

The CGM C13000HE generator is equipped with electric start with 12 V battery but also with manual recoil starter and with a low fuel consumption, in fact it consumes only 4,8 liters/hour at 75% of the load with an autonomy up to 3,1 hours.

This C13000HE generator is perfect for outdoor use such as hobbyist use. Also available in electric start and automatic start panel versions with ATS.

The CGM C13000HE generator is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, campgrounds, hobbies, construction sites, etc. The C13000HE generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical features of CGM C13000HE generator:

Phase type: Single phase
Maximum power: 11.8 KW
Continuous power: 10.8 KW
Maximum power: 13.2 KVA
Continuous power: 12 KVA
Fuel: Gasoline
Voltage: 230 V
Frequency: 50 Hz
Motor: HONDA GX630
Emissions standard: STAGE V
Alternator: LINZ - NSM
Alternator Type: Self-excited, brushless
Engine RPM: 3000 rpm
Start: Electric
Voltage Regulator System: AVR
Consumption: 4.8 Lt/h at 75% load
Tank capacity: 15 Lt
Autonomy: 3.1 h at 75% load
Length: 910 mm
Width: 580 mm
Height: 640 mm

Weight: 125 Kg

Discover the full range reserved for [generator](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	
Continuous power single phase (KW)	10.8
Maximum power single phase (KVA)	13.2
Continuous power single phase (KVA)	12
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	HONDA GC160
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Engine capacity (cm ³)	
Number cylinders	2
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	15
Consumption (L/h)	4.8
Running time (h)	3.1
Length (mm)	910
Width (mm)	580
Height (mm)	640
Dry weight (Kg)	
Silenced	No
Super silenced	No
Product type	Generator

ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda
