



CGM C11000TE

Reference: CGM C11000TE

CGM C11000TE Three-phase generator 10KVA

CGM C11000TE Three-phase generator 10KVA with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C11000TE is composed of a Made in Italy Linz or NSM alternator, self-excited with brushes and with AVR voltage regulator.

The CGM C11000TE generator is equipped with electric start with 12V battery but also with manual recoil starter and with a low fuel consumption, in fact it consumes only 2,2 liters/hour at 75% of the load for an autonomy up to 3 hours of operation. This CGM C11000TE generator set is perfect for outdoor use such as hobby use.

The CGM C11000TE generator is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, campgrounds, hobbies, construction sites etc. The CGM C11000TE generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical features of CGM C11000TE:

Type of phase: Singlephase / Threephase
Maximum singlephase power: 3.6 KVA / 3 KW
Continuous singlephase power: 3.3 KVA / 2.6 KW
Maximum threephase power: 11 KVA / 8.8 KW
Continuous threephase power: 10 KVA / 8 KW
Fuel: Petrol
Voltage: 230/400 V
Frequency: 50 Hz
Motor: BRIGGS & STRATTON 16HP
Motor RPM: 3000 RPM
Boosting: Electric
Voltage regulator system: AVR
Consumption: 3.8 Lt/h at 75% load
Tank capacity: 8.5 Lt
Autonomy: 2.2 h at 75% load
Length: 910 mm
Width: 580 mm
Height: 640 mm
Weight: 125 Kg

Discover the full range reserved for [generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits

your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	3
Continuous power single phase (KW)	2.6
Maximum power single phase (KVA)	
Continuous power single phase (KVA)	3.3
Maximum power three phase (KW)	8.8
Continuous power three phase (KW)	8
Maximum power three phase (KVA)	11
Continuous power three phase (KVA)	10
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE
Engine	Briggs&Stratton
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Engine capacity (cm ³)	480
Number cylinders	2
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	
Consumption (L/h)	3.8
Running time (h)	2.2
Length (mm)	910
Width (mm)	580
Height (mm)	64
Dry weight (Kg)	

Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Briggs&Stratton
