



## CGM C13000T

Reference: CGM C13000T

### CGM C13000T Three-phase generating set 12KVA

CGM C13000T Three-phase generator 12KVA with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C13000T generator is composed of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator.

The CGM C13000T generator is equipped with manual recoil start and low fuel consumption, in fact it consumes only 4.3 liters/hour at 75% of the load for an autonomy of up to 3 hours of operation.

This CGM C13000T is perfect for outdoor use such as hobby use. It is also available in a version with electric key start and with a panel for automatic start with ATS.

The CGM C13000T is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, campgrounds, hobbies, construction sites, etc. The CGM C13000T generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

#### Technical specifications of CGM C13000T:

Type of phase: Singlephase / Threephase  
Maximum singlephase power: 4.4 KVA / 3.5KW  
Continuous singlephase power: 4 KVA / 3.2 KW  
Maximum threephase power: 13.2 KVA / 10.5 KW  
Continuous threephase power: 12 KVA / 9.6 KW  
Fuel: Petrol  
Voltage: 230/400 V  
Frequency: 50 Hz  
Motor: BRIGGS & STRATTON 18HP  
Engine revolutions: 3000 rpm  
Starting: Manual  
Voltage regulator system: AVR  
Consumption: 4.3 Lt / h at 75% of the load  
Capacity tank: 8.5 Lt  
Autonomy: 2 h at 75% of the load  
Length: 910 mm  
Width: 580 mm  
Height: 640 mm  
Weight: 111 Kg

Discover the full range reserved for [generator](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

## Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	3.5
Continuous power single phase (KW)	3.2
Maximum power single phase (KVA)	
Continuous power single phase (KVA)	4
Maximum power three phase (KW)	
Continuous power three phase (KW)	
Maximum power three phase (KVA)	13.2
Continuous power three phase (KVA)	
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	
Engine	Briggs&Stratton
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm <sup>3</sup> )	570
Number cylinders	2
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	
Consumption (L/h)	4.3
Running time (h)	2

Length (mm)	910
Width (mm)	580
Height (mm)	640
Dry weight (Kg)	111
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Briggs&Stratton