



## CGM CX7000

Reference: CX7000

### GENERATOR CGM CX7000 SINGLE PHASE 7KVA AVR

Generator CGM CX7000 single-phase 7KVA with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with sturdy rain cover and vibration dampers. The CGM CX7000 generator set is composed of a Made in Italy Linz or NSM alternator, self-excited without brushes and with an AVR voltage regulator. The AVR regulator allows the voltage to be stabilized and does not ruin the connected sensitive devices. The CGM CX7000 generator set is equipped with manual recoil start and low fuel consumption, in fact it consumes only 2 liters/hour at 75% load. This generator set CX7000 is perfect for outdoor use such as for hobby use.

The CGM CX7000 generator set is part of the DELUXE series and is easily adaptable to various uses such as homes, mobile facilities, camping, hobbies, construction sites, etc.. The CX7000 generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

#### Technical features of CGM CX7000 generator:

Phase type: Single phase  
Maximum power: 6.9 KW  
Continuous power: 6.3 KW  
Maximum power: 7.7 KVA  
Continuous power: 7KVA  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Engine: HONDA GX390  
Engine revs: 3000 rpm  
Starting: Manual  
Voltage regulator system: AVR  
Consumption: 2 Lt/h at 75% of the load  
Tank capacity: 6.1 Lt  
Autonomy: 3 h at 75% load  
Length: 825 mm  
Width: 550 mm  
Height: 530 mm  
Weight: 82 Kg

Discover the full range reserved for [generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.9
Continuous power single phase (KW)	6.3
Maximum power single phase (KVA)	7.7
Continuous power single phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A 3P CEE - 1 x 230V SCHUKO
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm <sup>3</sup> )	389
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	6.1
Consumption (L/h)	2
Running time (h)	3
Length (mm)	825
Width (mm)	550
Height (mm)	530
Dry weight (Kg)	82
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda