



CGM CX5000T

Reference: CGM CX5000T

Generator Three-phase CGM CX5000T 5KVA AVR

Generator CGM CX5000T 5 KVA with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with sturdy rain cover and vibration dampers. The CGM CX5000T generator is composed of a Made in Italy Linz or NSM alternator, self-excited with brushes and with an AVR regulator. The AVR regulator allows to stabilize the voltage and does not ruin the connected sensitive devices. The CGM CX5000T generator is equipped with manual recoil start and low fuel consumption, in fact it consumes only 1.6 liters/hour at 75% load. This CX5000T generator set is perfect for outdoor use such as hobby use. The CGM CX5000T generator is part of the DELUXE series and is easily adaptable to various uses such as homes, mobile homes, campsites, hobbies, construction sites, etc.. The CX5000T generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical specifications of CGM CX5000T generator set:

Type of phase: Singlephase / Threephase
Maximum singlephase power: 1.8 KVA / 1.6 KW
Continuous singlephase power: 1.6 KVA / 1.3 KW
Maximum threephase power: 5.5 KVA / 4.8 KW
Continuous threephase power: 5 KVA / 4 KW
Fuel: Petrol
Voltage: 230/400 V
Frequency: 50 Hz
Motor: HONDA GX270
Engine rpm: 3000 rpm
Starting: Manual
Voltage regulator system: AVR
Consumption: 1.6 Lt / h at 75% of load
Tank capacity: 15 Lt
Autonomy: 9.4 h at 75% of the load
Length: 825 mm
Width: 550 mm
Height: 530 mm
Weight: 68 Kg

Discover the full range reserved for [generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	1.6
Continuous power single phase (KW)	1.3
Maximum power single phase (KVA)	1.8
Continuous power single phase (KVA)	1.6
Maximum power three phase (KW)	4.8
Continuous power three phase (KW)	4
Maximum power three phase (KVA)	
Continuous power three phase (KVA)	5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE - 1 x 230V SCHUKO
Engine	HONDA GX270
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm ³)	270
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	15
Consumption (L/h)	1.6
Running time (h)	9.4
Length (mm)	825
Width (mm)	550
Height (mm)	530
Dry weight (Kg)	68
Silenced	No
Super silenced	No
Product type	Generator

ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda
