



## CGM CX7000T

Reference: CGM CX7000T

### Generator Three-phase CGM CX7000T 7KVA AVR

Generator CGM CX7000T 7KVA three-phase with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with sturdy rain cover and vibration dampers. The CGM CX7000T generator set is composed of a Made in Italy Linz or NSM alternator, self-excited with brushes and with an AVR regulator. The AVR regulator allows to stabilize the voltage and does not ruin the connected sensitive devices. The CGM CX7000T generator set is equipped with manual recoil start and low fuel consumption, in fact it consumes only 2 liters/hour at 75% load. This CX7000T generator set is perfect for outdoor use such as hobby use. The CGM CX7000T generator is part of the DELUXE series and is easily adaptable to various uses such as homes, mobile homes, camping, hobbies, construction sites, etc.. The CX7000T generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

#### Technical characteristics of CGM CX7000T generator:

Type of phase: Singlephase / Threephase  
Maximum singlephase power: 2.5 KVA / 2 KW  
Continuous singlephase power: 2.3 KVA / 1.8 KW  
Maximum threephase power: 7.7 KVA / 6.1 KW  
Continuous threephase power: 7 KVA / 5.6 KW  
Fuel: Petrol  
Voltage: 230 V / 400 V  
Frequency: 50 Hz  
Motor: HONDA GX390  
Engine revolutions: 3000 rpm  
Starting: Manual  
Voltage regulator system: AVR  
Consumption: 2 Lt / h at 75% of load  
Tank capacity: 15 Lt  
Autonomy: 7.5 h at 75% of the load  
Length: 825 mm  
Width: 550 mm  
Height: 530 mm  
Weight: 76 Kg

Discover the entire range reserved for [generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data not binding.

## Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	2
Continuous power single phase (KW)	2.3
Maximum power single phase (KVA)	2.5
Continuous power single phase (KVA)	1.8
Maximum power three phase (KW)	6.1
Continuous power three phase (KW)	5.6
Maximum power three phase (KVA)	7.7
Continuous power three phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE - 1 x 230V SCHUKO
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm <sup>3</sup> )	389
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	15
Consumption (L/h)	2
Running time (h)	7.5
Length (mm)	825
Width (mm)	550
Height (mm)	530
Dry weight (Kg)	76
Silenced	No
Super silenced	No

---

Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda

---