



MARELLIMOTORI ALTERNATOR 17,5KVA MXB-E 160 MA4

Reference: MXB-E 160 MA4

MARELLIMOTORI MXB-E 160MA4 ALTERNATOR 17.5KVA THREE-PHASE AVR

MARELLIMOTORI MXB-E 160MA4 is a **Alternator** with a power of 17.5KVA 8KW, this unit has a self-exciting and self-regulating Brushless operation.

The MXB-E 160MA4 is designed to operate at frequency 50 or 60 HZ, the possibility to work on these two frequencies makes it possible to apply it for any service voltage increasing its versatility, for correct operation it is only necessary to verify that the voltage regulator settings are correct for the intended use.

MXB-E 160MA4 can be equipped with a wide assortment of accessories to meet the customer's needs.

The MarelliMotori Alternator is supplied with 12 terminals (7 terminals), unless specific requests from the customer. Normally it is possible to connect both series and parallel star alternator, in case you want to change the connections it is necessary to verify the connection of the AVR.

MXB-E 160MA4 threephase can be used as single-phase as required. MarelliMotori MXB-E 160MA4 is a 17.5KVA alternator equipped with AVR type M00FA122A - MARK VX, suitable for synchronous generators of MARELLIMOTORI construction. The regulator is suitable for operation on both three-phase generators and single-phase generators, allowing a fast, precise and reliable setup.

The M00FA122A is an electronic board designed by MarelliMotori, it is protected by a polyurethane resin that preserves the device from humidity, dust, aggressive environments; the voltage regulator serves to make the current stable, thus avoiding damaging the equipment connected to it, especially electronic equipment such as computers or smartphones. This AVR can be inserted in such a way as to automatically adjust the voltage and possibly also the frequency and / or electrical current according to the set values.

The AVR designed by MarelliMotori is internally equipped with a radio noise filter, which allows to contain radio noise emitted by MarelliMotori generators within the limits set by the European regulations for industrial environments

The AVR is equipped with an internal protection fuse (5 A, 500 V), which intervenes in case of regulator failures or very high overloads in the excitation circuit.

Select the alternator that matches the **technical specifications you require**, visit our [dedicated section](#) to understand how.

TECHNICAL FEATURES OF THE ALTERNATOR 17.5KVA THREEPHASE MXB-E 160MA4

Phase type: Threephase
Maximum power 50Hz: 17.5 KVA
Maximum power 50Hz: 14.0 KW
Maximum power 60Hz: 21.9 KVA

Maximum power 60Hz: 17.5 KW
Frequency: 50 - 60Hz
Voltage: 400 V / 480 V
Protection Degree: IP23
A alternator revolutions: 1500 / 1800 rpm
Number of poles: 4
Yield: 81.8%
Weight: 102.0 Kg
Constant speed alternator
Voltage regulator: AVR

Are you looking for a product with different characteristics? [HERE](#) you can find the whole range **MARELLIMOTORI** and other specialized brands.

Images and technical data not binding and subject to change by the manufacturer

Technical Sheet

Phase	Single phase / Three phase
Maximum power three phase (KW)	
Maximum power three phase (KVA)	17.5
Frequency (Hz)	50 / 60
Voltage (V)	400
Engine rpm (rpm)	1500
Poles	4
Efficiency (%)	81.8
Protection degree	IP23
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	102