



GENMAC Click G5500HO GENERATOR 5,8KVA

Reference:

GENMAC Click G5500HO GENERATOR 5,8KVA

The **generator Genmac Click G5500HO** three phase has a Honda gasoline feeding engine capable of delivering a power of 5,8KVA with the possibility of connection to optional AVR.

The GENMAC Click G5500HO generator is equipped with a Honda Stage V engine certified for mobile use in the EU, but which does not comply with others criteria of the regulation. The engine is feeding by gasoline by means of a tank with a capacity of 5,3 liters for an autonomy of about three and a half hours, complete with manual starter.

The Genmac 5,8KVA generator is equipped with a front control panel for portable units, with manual start and oil level sensor.

In combination with the generator it is possible to request the handling kit specifically designed for the selected model, for a more comfortable transport before the installation on the working lug.

The 5,8KVA generator is equipped with capacitor voltage regulator, on request it is possible to supply it with AVR voltage regulator.

Optional AVR regulator

The AVR brings a significant improvement in output voltage stability; this is particularly useful with commonly used machines with reactive load, such as refrigerators, freezers, air conditioners and garden machines. This will increase the life of your devices.

The optional AVR is a device that keeps the out voltage more constant and less load-dependent. Thanks to this technology there are fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

Technical features of generator 5,8KVA Genmac Click G5500HO

Supply: Gasoline
Start: manual recoil
Phase type: Singlephase / Threephase
Continuous singlephase power : 1.6 KVA / 1.5 KW
Maximum singlephase power: 2 KVA / 1.8 KW
Threephase continuous power: 5,0KVA / 4,0KW
Threephase maximum power: 5,8KVA / 4,6KW
Motor: Honda GX270
Socket panel: 1 x Schuko 230 V - 1 x 16 A 400 V
Voltage: 230 / 400V
Frequency: 50 Hz
3000 rpm

Tank: 5,3 Lt.
 Autonomy @ 75%: 3,2 h fixed rpm
 Starting: Manual
 Length (mm): 740
 Width (mm): 500
 Height (mm): 530
 Dry weight (Kg): 71

If you are looking for another product then you can consult on our catalog other [terrestrial gene-groups](#).

Images and technical data are not binding and may be subject to review

Technical Sheet

| Phase | Single phase / Three phase |
|-------------------------------------|----------------------------|
| Maximum power single phase (KW) | 1.8 |
| Continuous power single phase (KW) | 1.5 |
| Maximum power single phase (KVA) | 2 |
| Continuous power single phase (KVA) | 1.6 |
| Maximum power three phase (KW) | 4.6 |
| Continuous power three phase (KW) | 4 |
| Maximum power three phase (KVA) | 5.8 |
| Continuous power three phase (KVA) | 5 |
| Fuel | Gasoline |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 / 400 |
| Engine | HONDA GX270 |
| Engine rpm (rpm) | 3000 |
| Starting system | Pull starter |
| Cooling | Air |
| Fuel tank capacity (L) | 5.3 |
| Running time (h) | 3.2 |
| Length (mm) | 740 |
| Width (mm) | 500 |
| Height (mm) | 530 |
| Dry weight (Kg) | 71 |
| Product type | Generator |
| ATS Switch device | No ATS |

Voltage regulator

AVR (optional)