



## GENMAC Combipro RG7300HAC-M5 GENERATOR 7,1KVA

Reference:

### GENMAC COMBIPRO RG7300HAC-M5 SINGLE-PHASE GENERATOR 7,1KVA

The generator Genmac Combipro RG7300HAC-M5 single phase is equipped with a Honda gasoline powered engine capable of delivering a power of 7,1KVA with capacitor voltage regulator (AVR optional).

The Generators of the **Genmac Combipro RG7300 series** are among the most **silent** in their category, thanks to the side closing panels and the oversized muffler.

These power generators are built with a **compact and robust** structure with sturdy **wheels and handle** integrated into the frame, which makes them handy and easily transportable. The 300mm diameter wheels with double reinforcement, with which Combipro generators are equipped, are integrated in the structure and the retractable handle can be folded to avoid unnecessary hindrance when not in use. On the frontal part there is also a full length support to avoid sinking into the ground.

The front panel of the Genmac 7,1KVA generator is protected by a canopy and comes complete with a back panel that provides **water protection and insulation**.

The Genmac RG7300 7,1KVA generators are equipped with a **25-liter tank** with a large cap that is convenient to unscrew even with work gloves, filter and **fuel level indicator**. There is also a manual fuel circuit shut-off tap to prevent fuel leakage.

### AVR Voltage Regulator

All models in the Genmac Combipro series are available with optional AVR voltage regulator. The AVR is a device that allows to **maintain the output more constant and less load-dependent**. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

**The model equipped with AVR card is highly recommended**, as it guarantees a significant improvement in the stability of the output voltage; this feature makes the generators particularly suitable with common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you can enjoy greater stability and thus increase the life of your devices.

#### TECHNICAL FEATURES OF GENERATOR GENMAC COMBIPRO RG7300HAC-M5

Voltage regulator : capacitor (AVR Optional)  
Power supply: Gasoline  
Firing: Electric  
Phase type: Single phase  
Continuous power: 6.4KVA / 5.8KW  
Maximum power: 7.1KVA / 6.4KW  
Motor: Honda iGX390  
Socket panel: 1 x schuko 230V - 1 x 16A 230V - 1 x 32A 230 V

Emission standard: Stage V  
Voltage: 230V  
Frequency: 50 Hz  
3000 revolutions per minute  
Tank: 25 Lt.  
Autonomy @ 75%: 14 h fixed revolutions  
Boosting: Manual  
Length (mm): 800  
Width (mm): 640  
Height (mm): 700  
Dry weight (Kg): 116

If you are looking for another product then you can see on [our catalog](#) other generator

Images and technical data not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.4
Continuous power single phase (KW)	5.8
Maximum power single phase (KVA)	6.4
Continuous power single phase (KVA)	7.1
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	Honda iGX390, 4 stroke, OHV
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Cooling	Air
Poles	2
Fuel tank capacity (L)	25
Running time (h)	14
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	
Width (mm)	
Height (mm)	700
Dry weight (Kg)	116
Silenced	Yes
Super silenced	No

---

ATS Switch device	ATS Included
Voltage regulator	AVR (optional)
Engine manufacturer	Honda

---