



VISA P15SG GENERATOR 17KVA SINGLE/THREE PHASE AVR

Reference: P 15 SG

VISA P15SG GENERATOR 17KVA SINGLE/THREE PHASE AVR

The VISA P15SG single-phase/ three-phase generator is equipped with a Perkins 403A-15G2 Diesel engine, and is capable of delivering a maximum power of 17 KVA, complete with AVR voltage regulator.

The VISA P15SG genset is equipped with electric start, manual or automatic with 12 V battery, and is equipped with Comap AMF 25 control unit that allows to display of all electrical parameters of the engine and generator, functions, states of the genset, manage the genset entirely and display, in case they occur, errors or alarms of the system.

The Visa P15SG is equipped with a large fuel tank, allowing extended operation without the need for frequent refueling. This is particularly advantageous in situations where continuity of power supply is essential, such as during blackouts or power outages.

The Visa P15SG generator is also designed with an advanced silencing system, which reduces the noise produced during its operation. This makes it ideal for use in noise-sensitive areas or in situations where low noise is required, such as in residential or hospital facilities.

Thanks to the AVR voltage regulator included with the genset, the VISA P15SG is able to deliver "clean" current and voltage with an accuracy of less than one percent, this ensures that the user, can safely connect any type of electrical and electronic device. The VISA P15SG genset guarantees efficient and quiet operation thanks to the Perkins 403A-15G2 Engine motor, which allows it to deliver a maximum power of 17 KVA.

The versatility of the Visa P15SG is another of its strengths. It can be used in a variety of settings, such as homes, stores, farms, construction sites and more. Its ability to operate in both single-phase and three-phase modes allows it to adapt to different power supply needs.

The Visa P15SG generator comes complete with:

- Differential Circuit Breaker;
- Liquid collection tank with level sensor;
- Motor heater;
- Oil extraction pump

ATS AUTHOMATIC TRANSFER SWITCH (OPTIONAL)

The genset is prepared for the use of Authomatic Transfer Switch ATS. Thanks to which you will no longer have to worry about blackouts because if the power grid goes out, this panel can automatically start the generator and allow you to continue your activity without losing your work data.

TECHNICAL FEATURES VISA P15SG

Phase Type: Single Phase / Three Phase
Maximum power: 17 KVA / 13 KW
Continuous power: 15 KVA / 12 KW
Fuel: Diesel
Voltage: 230 / 400 V
Frequency: 50 Hz
Engine: Perkins 403A-15G2
Emission standard: Not Emitted
Number of cylinders: 3
Engine speed: 1500 rpm
Starter: Electric
Control unit: Comap AMF 25
Voltage regulator: AVR
Socket panel: Terminal block (Power socket)
Tank capacity: 50 Lt
Consumption: 3.1 Lt/h at 75% load
Autonomy: 16.1 h at 75% load
Acoustic pressure: 68 dB(A) @ 7m
Length: 1802 mm
Width: 752 mm
Height: 1130 mm
Net weight: 588 kg

Are you looking for a generator with different technical characteristics? [HERE](#) you can find the area dedicated to VISA generator or other specialized brands.

The images are purely indicative.

Technical Sheet

Phase	Single phase / Three phase
Maximum power three phase (KW)	13
Continuous power three phase (KW)	12
Maximum power three phase (KVA)	17
Continuous power three phase (KVA)	15
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	Terminal box
Engine	Perkins 403A-15G2
Emissions Regulations	Not Emitted
Engine rpm (rpm)	1500
Starting system	Electric
Number cylinders	3
Cooling	Water
Alternator	STAMFORD S0L1-P
Fuel tank capacity (L)	50

Consumption (L/h)	3.1 at 75% load
Running time (h)	16.1 at 75% load
Acoustic pressure	68 dB(A) at 7 m
Length (mm)	1802
Width (mm)	752
Height (mm)	1130
Dry weight (Kg)	588
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Perkins