



## USED CS18000T GENERATORE MONOFASE / TRIFASE STAGE V 19,2KVA

Reference: CS18000T-USED

### USED GENERATOR CS18000T SINGLE-PHASE / THREE-PHASE STAGE V 19.2KVA

Used Generator CS18000T three-phase 19.2 KVA with BRIGGS & STRATTON engine powered by Petrol STAGE V at 3000 rpm, compact and easy to use.

The Used generator CS18000T is composed of a NSM Made in Italy alternator, self-excited without brushes and with voltage regulator **AVR**. The generator is equipped with electric starter with battery that allows for practical and fast use even when cold. The generator has low fuel consumption, in fact it consumes only 6.5 liters/hour at 75% of the load.

The Used CS18000T generator is part of the QUIET series because thanks to the canopy it has low noise emissions and is super-silenced. This generator is 3000 rpm, with a BRIGGS & petrol engine STRATTON electric start with key and battery.

Technical characteristics of the Used generator CS18000T:

Phase type: Single phase / Three phase  
Continuous power single phase: 5.8 KVA / 4.6 KW  
Maximum power single phase: 6.4 KVA / 5.1 KW  
Continuous power three phase: 17.5 KVA / 14 KW  
Maximum power three phase: 19.2 KVA / 15.3 KW  
Power factor cos  $\phi$ ?: 0.8  
VAC voltage: 230 / 400 V  
Frequency (Hz): 50  
Voltage regulator: AVR  
Starting panel: Manual / Automatic  
Engine: BRIGGS & STRATTON 31HP  
Revolutions per minute RPM: 3000  
Power supply: Petrol  
Emissions standard: STAGE V  
Tank capacity: 60 l  
Consumption @ 75 % of load: 6.5 l/h  
Autonomy @ 75 % of load: 9.2 h  
Sound pressure: 72 dB(A) @ 7m  
Length: 1200 mm  
Width: 730 mm  
Height: 930 mm  
Net weight: 280 Kg

Manual electrical panel with:  
n.1 CEE socket 16A 3P 230V  
n.1 CEE socket 32A 5P 400V

Main switch  
 connector for ATS  
 hour counter

Discover the entire range of [generator](#) on our catalog to find the one that best suits your needs.

Images and technical data are not binding. Please always consult the technical data sheet released by the manufacturer. Manel Service does not assume responsibility for any changes made by the manufacturer.

## Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	5.1
Continuous power single phase (KW)	4.6
Maximum power single phase (KVA)	6.4
Continuous power single phase (KVA)	5.6
Maximum power three phase (KW)	15.3
Continuous power three phase (KW)	14
Maximum power three phase (KVA)	19.2
Continuous power three phase (KVA)	17.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 230V 16A 3P CEE - 1 x 400V 32A 5P
Engine	BRIGGS & STRATTON 31HP
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale / Automatico
Engine capacity (cm <sup>3</sup> )	896
Number cylinders	2
Cooling	Air
Alternator	NSM, made in Italy
Fuel tank capacity (L)	60
Consumption (L/h)	6.5 @ 75 % del carico
Running time (h)	9.2 @ 75 % del carico
Length (mm)	1200

---

Width (mm)	730
Height (mm)	930
Dry weight (Kg)	280
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Briggs&Stratton
Video	MKDdx7hAnHc

---