



DOMETIC TEC 60 Petrol Single Phase Generator 7000 Watts 230 V AC Inverter

Reference: 9102900229

Despite its continuous power of 6000 watts, it is surprisingly quiet and economical. Like all other TEC series generators, the speed varies according to requirements. Proven inverter technology ensures pure sinusoidal voltage and high performance.

Quality characteristics

- Remote Control
- 12 V voltage for battery charger
- Automatic switch-off in case of low oil level
- Electric Ignition
- Overload and short circuit protection
- Sound absorbing housing
- High continuous power
- Suitable as a power source for all Dometic air conditioners
- Low consumption
- Remote control for displaying all the parameters of working
- Fueled with unleaded petrol

Certifications

EC, E13

Non-binding images and technical data.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	7
Continuous power single phase (KW)	6.2
Fuel	Gasoline

Frequency (Hz)	50
Voltage (V)	230
Engine	Honda GX390
Starting system	Manual / Electric
Consumption (L/h)	3..7
Acoustic power	90 dB(A)
Acoustic pressure	66 dB(A) at 7 m
Length (mm)	626
Width (mm)	446
Height (mm)	547
Dry weight (Kg)	102
Silenced	Yes
Super silenced	Yes
Brushes	No
Voltage regulator	Inverter
Engine manufacturer	Honda