



PRAMAC PX4000 2.7 KW generator set with AVR

Reference: PK222SX1000

PRAMAC PX4000 2.7 KW AVR GENERATOR SET

The PRAMAC PX4000 single-phase 2.7 KW generator set is equipped with a petrol engine running at 3000 rpm. The PRAMAC PX4000 generator set features a manual recoil starter with a self-winding mechanism. The alternator of the PRAMAC PX4000 is equipped with an AVR voltage regulator. The Pramac petrol engine makes the PX4000 generator set highly reliable, as it is built and designed with high-quality materials.

Thanks to its very low weight and compact dimensions, it is easy to transport wherever it is needed most. The PRAMAC PX4000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor hobby jobs.

Technical characteristics of the PRAMAC PX4000 AVR generator set:

- Maximum single-phase power: 2.7 KW
- Continuous single-phase power: 2.3 KW
- Fuel: Petrol
- Voltage: 230 V
- Frequency: 50 Hz
- Engine: PRAMAC AP170F
- Starting: Recoil (manual pull start)
- Consumption: 1.29 Lt/h at 100% load
- Length: 600 mm
- Width: 439 mm
- Height: 588 mm
- Weight: 53 Kg
- Voltage regulator: AVR

CONTROL PANEL

Controls:

- Ignition key: OFF - ON

Instruments:

- Voltmeter
- Ammeter
- Frequency meter
- Fuel level indicator

Protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

2 SCHUKO 230V 16A IP54

The PRAMAC PX4000 single-phase generator is a petrol generator and represents one of Pramac's latest innovations to ensure a high level of quality and performance at a competitive price. The PRAMAC PX4000 generator set is compact, efficient, and easy to use. It is perfect for all your semi-professional applications.

If you are looking for a generator set like the PRAMAC PX4000 AVR single-phase, we recommend consulting our catalogue of terrestrial generator sets to find the one that best suits your needs.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2.7
Continuous power single phase (KW)	2.3
Maximum power single phase (KVA)	3
Continuous power single phase (KVA)	2.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A IP54 SCHUKO
Engine	PRAMAC AP170F, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Pull starter
Engine capacity (cm ³)	208
Oil capacity (L)	0.6
Cooling	Air
Poles	2
Fuel tank capacity (L)	18.5
Consumption (L/h)	0.96 at 75% of the load / 1.29 at 100% of the load
Running time (h)	19.27 at 75% of the load / 14.34 at 100% of the load
Acoustic power	96 dB(A)
Acoustic pressure	72 dB(A) at 7 m
Length (mm)	600
Width (mm)	439
Height (mm)	588

Dry weight (Kg)	53
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	PRAMAC
Video	0F1btCzOIWA
