



PRAMAC PX8000 GENERATOR SINGLE PHASE / THREE PHASE 6 KVA AVR

Reference: PK472TX2000

PRAMAC PX8000 GENERATOR SINGLE PHASE / THREE PHASE 6 KVA AVR

PRAMAC PX8000 singlephase / threephase generator with PRAMAC AP190F engine powered by gasoline, capable of delivering a power of 6 KVA complete with AVR voltage regulator.

The PRAMAC PX8000 generator is equipped with electric start with battery, but it is also equipped with a rope recoil starter for manual start. The alternator of the PRAMAC PX8000 is with AVR voltage regulator.

The gasoline engine PRAMAC AP190F makes the generator very reliable as it has been built and designed using high quality materials.

Due to its very low weight and compact size, it is convenient to carry where you need it most. This generator is suitable for outdoor use in small construction sites or for small outdoor work for hobby use.

This gasoline generator represents one of the latest innovations of Pramac to ensure a high level of quality and performance at an attractive price. The PRAMAC PX8000 is compact, efficient and easy to use. The genset is perfect for all your semi-professional applications.

TECHNICAL FEATURES PRAMAC PX8000:

Phase type: Single-phase/Three-phase

Single-phase continuous power use: 1.6 KVA / 1.2 KW

Maximum single-phase power: 2 KVA / 1.5 KW

Three-phase continuous use power: 5 KVA / 4 KW

Maximum three-phase power: 6 KVA / 4.8 KW

Motor: Pramac SR190F

Motor speed: 3000 rpm

Emissions regulations: Not emitted

Starter: Electric / Manual

Fuel: Petrol

Voltage: 230 / 400 V

Frequency: 50 Hz

Socket panel: 1 x SCHUKO 230V 16A / 1 x 2P+E CEE 230V 16A / 1 x 3P+N+E CEE 400V 16A

Tank capacity: 27 l

Acoustic power (LWA) dBA 97

Acoustic pressure: 69 dB(A) @ 7 m

Length: 727 mm

Width: 515 mm

Height: 670 mm

Dry weight: 97 Kg

Autonomy at 75% load h 13.11
 Autonomy at 100% load h 9.82

CONTROL PANEL

Controls:

- Start key: OFF - ON - START

Instrumentation:

- Voltmeter
- Ammeter
- Frequency meter
- Fuel level indicator

Protections:

- Thermal Protection
- Oil Guard (low oil level)

Sockets

- N.1 SCHUKO 230V 16A IP54
- N.1 2P+T CEE 230V 16A IP44
- N.1 3P+N+T CEE 400V 16A IP44

Are you looking for a generator with different technical features? [HERE](#) you can find the area dedicated to PRAMAC generator or other specialized brands.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	1.6
Continuous power single phase (KW)	1.2
Maximum power single phase (KVA)	2
Continuous power single phase (KVA)	1.5
Maximum power three phase (KW)	4.8
Continuous power three phase (KW)	4
Maximum power three phase (KVA)	6
Continuous power three phase (KVA)	5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A

SCHUKO

Engine	PRAMAC SR190F, naturally aspirated
Emissions Regulations	Stationary Use
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Elettrico
Engine capacity (cm ³)	420
Oil capacity (L)	1.1
Cooling	Air
Poles	2
Fuel tank capacity (L)	27
Consumption (L/h)	2.75
Running time (h)	9.8
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	727
Width (mm)	515
Height (mm)	670
Dry weight (Kg)	97
Silenced	Yes
Super silenced	Yes
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	PRAMAC