



GENSET MG 50 H/A GENSET MG 50 H/A Generator StageV

Reference: MG 50 H/A -AVR

Generating Sets from 1 kVA to 2000 kVA with manual or automatic starting.
Thanks to such a wide range, GenSet is able to present specific solutions in the most diverse fields of application of the genset, both for continuous use and for emergency use in case of interruption of the main power supply.
All GenSet generating sets strictly comply with EC regulations on safety in use and control of polluting emissions.

The images are purely indicative.

Technical Sheet

| | |
|------------------------------------|-------------------------|
| Phase | Single phase |
| Maximum power single phase (KW) | 4 |
| Maximum power single phase (KVA) | 5 |
| Fuel | Gasoline |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 |
| Sockets configuration | 2 x monofase CEE 16 A |
| Engine | Honda GX 270 OHV |
| Engine rpm (rpm) | 3000 |
| Starting system | Electric |
| Engine capacity (cm ³) | 270 |
| Number cylinders | 1 |
| Cooling | Air |
| Alternator | Synchronous |
| Fuel tank capacity (L) | 6 |
| Consumption (L/h) | 2.2 at 75% of the load |
| Running time (h) | 2.72 at 75% of the load |
| Acoustic power | 99 dB(A) |

| | |
|---------------------|-----------------|
| Acoustic pressure | 74 dB(A) at 7 m |
| Length (mm) | 725 |
| Width (mm) | 515 |
| Height (mm) | 585 |
| Dry weight (Kg) | 76 |
| Silenced | No |
| Super silenced | No |
| ATS Switch device | Optional ATS |
| Voltage regulator | No |
| Engine manufacturer | Honda |