



HONDA EG 4500 CL Petrol Single-Phase D-Avr Generator 4.5 kW 5.6 kVA

Reference: EG4500CL

HONDA EG 4500 CL PETROL SINGLE-PHASE D-AVR GENERATOR 4.5KW 5.6KVA

Honda EG4500CL generator Continuing to maintain uninterrupted power supplies because a generator has damaged a tool or broken down is not a condition that can be tolerated.

Honda EG4500CL generator are the right tools. Ideal for sensitive electronic equipment as well as demanding commercial and rental applications, they are always ready for work, anywhere, anytime.

Technical Specifications HONDA EG4500CL:

Phase Type: Single Phase
Maximum power Single-phase (kW): 4.5
Single-phase continuous power (kW): 4
Maximum power single-phase (kVA): 5.6
Single-phase continuous power use (kVA): 5
Fuel: Petrol
Voltage (V): 230
Frequency (Hz): 50 Hz
Engine: Honda GX390T2
Type: 4-stroke, OHV, 1 cylinder
Starter: Manual
Autonomy: 9h 30
Consumption: 2.5 Lt/h
Length: 681 mm
Width: 530 mm
Height: 571 mm
Weight (Kg): 79.5
D-Avr
Current (A) 17.4
Displacement (cm³): 389
Engine revs: 3000

D-AVR

It is good to know that you can always count on the power of a Honda EG4500CL generator, produced through a digital automatic voltage regulator (D-AVR). This regulator is an improvement over the traditional AVR and provides smoother and more efficient power for sensitive electronic equipment, offering a stable clean energy waveform.

As autonomous as a day's work

With durations between 8 and 12 hours, Honda EG4500CL generators become reliable companions, ready to work every day of the week. Once in operation, they meet any demand, responding well even to load variations.

The practical fuel cap allows easy refueling without spilling: everything is always neat and tidy with a Honda EG4500CL generator.

The fuel tank cap also allows the fuel level to be checked without removing it, also offering significant time savings.

Fast and effective starting

Extremely convenient sockets and controls enable quick and easy starting and operation, particularly because the starter motor and starter device, fuel tank cap, switch, and plugs are all located on the same panel. This allows easy and convenient machine start-up and operation.

Oil Alert™

Don't forget that Oil Alert™ technology will automatically disengage the contact if the oil is below the safe level.

Smooth operation

Honda for the Honda EG4500CL generator has developed a unique engine support system with a durable steel frame. These rubber shock absorbers, placed on both sides of the engine and angled at 45°, significantly reduce engine vibration of an already quiet machine. Aesthetically beautiful, functionally effective.

Warranty

When you purchase a Honda EG4500CL generator you enjoy the exclusive benefit of a national or commercial warranty, provided that the service program is met.

Discover our huge range of generator sets by [clicking here!!](#)

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	4.5
Continuous power single phase (KW)	4
Maximum power single phase (KVA)	5.62
Continuous power single phase (KVA)	5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A CEE - 1 x 230V 32A CEE
Engine	Honda GX390 T2, 4 stroke, OHV
Engine rpm (rpm)	3000
Ignition	Transistorized
Starting system	Manuale
Engine capacity (cm ³)	389
Number cylinders	1
Cooling	Air
Alternator	Bipolar
Bore x stroke (mm)	88 x 64
Fuel tank capacity (L)	24
Consumption (L/h)	2.5

Running time (h)	9.5
Acoustic power	97 dB(A)
Acoustic pressure	81 dB(A)
Length (mm)	681
Width (mm)	530
Height (mm)	571
Dry weight (Kg)	79.5
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	iAVR
Engine manufacturer	Honda