



PRAMAC E8000 THREE PHASE

Reference: PA702TH1000

PRAMAC E8000 generator set Single-phase/Three-phase 6.6 KW

PRAMAC E8000 generator set single-phase/three-phase 6.6 KW with Honda GX390 engine at 3000 rpm in open version. The PRAMAC E8000 generator set single-phase/three-phase is equipped with manual recoil starter with self-winding mechanism. The PRAMAC E8000 generator set alternator is three-phase, with brushes with **compound** voltage regulator. The Honda engine makes this generator set **very reliable** as it is composed and built with high quality materials.

Thanks to its very low weight and its **compact dimensions** it is convenient to transport where you need it most. The PRAMAC E8000 single-phase/three-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC E8000 single-phase/three-phase generator:

Maximum power Single-phase: 3.2 KW
Continuous use power Single-phase: 2.96 KW
Maximum power Three-phase: 6.6 KW
Continuous use power Three-phase: 5.6 KW
Fuel: Petrol
Voltage: 230 V / 400 V
Frequency: 50 Hz
Engine: Honda GX390 Recoil
Starting: Recoil
Consumption: 2.9 Lt/h at 100% load
Length: 750 mm
Width: 578 mm
Height: 531 mm
Weight: 80 Kg
Compound

CONTROL PANEL

Controls:

- Switch: OFF - ON
- Ignition: Recoil start
- Fuel tap

Standard protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

- N.1 SCHUKO 230V 16A IP54
- N.1 2P+T CEE 230V 16A IP44
- N.1 3P+N+T CEE 400V 16A IP44

The PRAMAC E8000 generator is a single-phase/three-phase petrol generator developed by Pramac to guarantee a high level of quality and performance at an attractive price. The PRAMAC E8000 generator is ideal for intensive applications, characterized by a robust structure with a load-bearing tubular frame that simplifies both its use and maintenance operations.

The E8000 generator is the essential machine to satisfy professional applications.

If you are looking for a generator set like the PRAMAC E8000 single-phase/three-phase generator then we recommend you browse our catalogue of [terrestrial generator sets](#) to find the one that best meets your needs.

Images and technical data are not binding. Please always consult the technical data sheet released by the manufacturer. Manel Service does not assume responsibility for any changes made by the manufacturer.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	3.2
Continuous power single phase (KW)	2.96
Maximum power single phase (KVA)	4
Continuous power single phase (KVA)	3.7
Maximum power three phase (KW)	6.6
Continuous power three phase (KW)	5.6
Maximum power three phase (KVA)	8.3
Continuous power three phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 3P+N+T CEE IP44 - 1 x 230V 16A SCHUKO IP54 - 1 x 230V 16A 2P+T CEE IP44
Engine	Honda GX390 Recoil, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm ³)	389

Oil capacity (L)	1.1
Cooling	Air
Alternator	With brushes
Poles	2
Fuel tank capacity (L)	6.1
Consumption (L/h)	2.1 at 75% of the load / 2.9 at 100% of the load
Running time (h)	2.9 at 75% of the load / 2.1 at 100% of the load
Acoustic power	97 dB(A)
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	750
Width (mm)	578
Height (mm)	531
Dry weight (Kg)	80
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Compound
Engine manufacturer	Honda