



PRAMAC E8000 SINGLE-PHASE

Reference: PA652SH1000

PRAMAC E8000 Single-phase 6.4 KW generator set

PRAMAC E8000 single-phase 6.4 KW generator set with Honda engine at 3000 rpm in open version. The PRAMAC E8000 single-phase generator set is equipped with a recoil starter with self-winding. The single-phase alternator of the PRAMAC E8000 generator set is brushless with a capacitor voltage regulator. The Honda engine makes this generator set **very reliable** as it is built and designed with high-quality materials.

Thanks to its frame, low weight and **compact dimensions** it is easy to transport where you need energy. The PRAMAC E8000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC E8000 single-phase generator:

Maximum power Single-phase: 6.4 KW
Continuous use power Single-phase: 5.5 KW
Fuel: Petrol
Voltage: 230 V
Frequency: 50 Hz
Engine: Honda GX390 Recoil
Starting: Recoil
Consumption: 2.9 Lt/h at 100% load
Length: 750 mm
Width: 578 mm
Height: 531 mm
Weight: 72 Kg

CONTROL PANEL

Controls:

- Switch: OFF - ON
- Ignition: Self-winding
- Fuel tap

Standard protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

- N.1 SCHUKO 230V 16A IP54
- N.1 2P+T CEE 230V 32A IP44

The PRAMAC E8000 generator is a petrol generator developed by Pramac to guarantee a high level of quality and performance at an attractive price. The PRAMAC E8000 generator is ideal for intense applications and is characterised by a robust structure with a load-bearing tubular frame, which simplifies both use and maintenance operations.

The E8000 generator is the essential generator to satisfy professional applications.

If you are looking for a generator like the PRAMAC E8000 single-phase generator, then we recommend that you browse our catalogue of [terrestrial generators](#) to find the one that best meets your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.4
Continuous power single phase (KW)	5.5
Maximum power single phase (KVA)	7.2
Continuous power single phase (KVA)	6
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A SCHUKO IP54 - 1 x 230V 32A 2P+T CEE IP44
Engine	Honda GX390 Recoil, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm ³)	389
Oil capacity (L)	1.1
Cooling	Air
Poles	2
Fuel tank capacity (L)	6.1
Consumption (L/h)	2.1 at 75% of the load / 2.9 at 100% of the load
Running time (h)	2.9 at 75% of the load / 2.1 at 100% of the load
Acoustic power	97 dB(A)
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	750
Width (mm)	578
Height (mm)	531
Dry weight (Kg)	72
Silenced	No
Super silenced	No

Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Capacitor
Engine manufacturer	Honda
