



PRAMAC ES3000 SINGLE-PHASE PETROL

Reference: PE242SH1000

PRAMAC ES3000 Single-phase generator set 2.6 KW

PRAMAC ES3000 single-phase generator set of 2.6 KW with a petrol-powered engine at 3000 rpm. The PRAMAC ES3000 generator set is equipped with manual recoil starter with self-winding. The PRAMAC ES3000 generator set is brushless and has a voltage regulator with capacitor. The Honda petrol engine makes the ES3000 generator set **very reliable** as it has been built and designed using top quality materials.

Thanks to its very low weight and its **compact dimensions** it is convenient to transport where you need it most. The PRAMAC ES3000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC ES3000 generator:

Maximum power Single-phase: 2.6 KW
Continuous use power Single-phase: 2.2 KW
Fuel: Petrol
Voltage: 230 V
Frequency: 50 Hz
Engine: Honda GX160
Starting: Recoil
Consumption: 1.2 Lt/h at 100% load
Length: 623 mm
Width: 409 mm
Height: 500 mm
Weight: 43 Kg

CONTROL PANEL

Controls:

- Switch: OFF - ON
- Ignition: Recoil start
- Fuel tap

Standard protections:

- Thermal protection
- Oil Guard (low oil level)

Protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

N.2 SCHUKO 230V 16A IP54

The PRAMAC ES3000 generator is a petrol generator developed by Pramac to ensure a high level of efficiency, quality and performance at an attractive price. The PRAMAC ES3000 generator is characterized by a sturdy structure with a load-bearing tubular frame and adequate steel sheet protections with a built-in oversized tank. The ES3000 generator is designed to satisfy long-lasting professional and intensive applications. If you are looking for a generator like the single-phase ES3000 generator, we recommend that you browse our catalogue of [terrestrial generators](#) to find the one that best meets your needs.

Images and technical data are not binding. Please always consult the technical data sheet released by the manufacturer. Manel Service does not assume responsibility for any changes made by the manufacturer.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2.6
Continuous power single phase (KW)	
Maximum power single phase (KVA)	2.9
Continuous power single phase (KVA)	2.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A IP54 SCHUKO
Engine	Honda GX160, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm ³)	163
Oil capacity (L)	0.6
Cooling	Air
Alternator	Brushless
Poles	2
Fuel tank capacity (L)	11
Consumption (L/h)	0.9 at 75% of the load / 1.2 at 100% of the load
Running time (h)	12.5 at 75% of the load / at 100% of the load
Acoustic power	96 dB(A)
Acoustic pressure	68 dB(A) at 7 m
Length (mm)	623
Width (mm)	409
Height (mm)	500
Dry weight (Kg)	43

Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Capacitor
Engine manufacturer	Honda
