



## PRAMAC ES4000 SINGLE-PHASE PETROL

Reference: PE292SH1000

### PRAMAC ES4000 Single-phase generator set 3.1 KW

PRAMAC ES4000 single-phase generator set 3.1 KW with petrol-powered engine at 3000 rpm. The PRAMAC ES4000 generator set is equipped with manual recoil starter with self-winding. The PRAMAC ES4000 generator set alternator is brushless and with voltage regulator with capacitor. The Honda petrol engine makes the ES4000 generator set **very reliable** as it has been built and designed using top quality materials.

Thanks to its very low weight and its **compact dimensions** it is convenient to transport where you need it most. The PRAMAC ES4000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

#### Technical characteristics of the PRAMAC ES4000 generator:

Maximum power Single-phase: 3.1 KW  
Continuous use power Single-phase: 2.6 KW  
Fuel: Petrol  
Voltage: 230 V  
Frequency: 50 Hz  
Engine: Honda GX200  
Starting: Recoil  
Consumption: 1.6 Lt/h at 100% of load  
Length: 623 mm  
Width: 409 mm  
Height: 500 mm  
Weight: 43 Kg

#### CONTROL PANEL

##### Controls:

- Switch: OFF - ON
- Ignition: Self-winding
- Fuel tap

##### Standard protections:

- Thermal protection
- Oil Guard (low oil level)

##### Protections:

- Thermal protection
- Oil Guard (low oil level)

##### Sockets:

N.2 SCHUKO 230V 16A IP54

The PRAMAC generator ES4000 is a single-phase petrol generator developed by Pramac to guarantee a high level of quality and performance at an attractive price. The PRAMAC ES4000 generator is built with a sturdy structure with a load-bearing tubular frame and adequate steel sheet protections with a built-in oversized tank.

The ES4000 generator is designed to satisfy long-lasting professional and intensive applications.

If you are looking for a generator like the ES4000 single-phase generator then we recommend you browse our catalogue of [gruppi elettrogeni-terrestri](#) to find the one that best suits your needs.

Images and technical data are not binding. Please always consult the technical data sheet issued by the manufacturer. Manel Service does not assume responsibility for any changes made by the manufacturer.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.1
Continuous power single phase (KW)	2.6
Maximum power single phase (KVA)	3.4
Continuous power single phase (KVA)	2.9
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A IP54 SCHUKO
Engine	Honda GX200, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm <sup>3</sup> )	196
Oil capacity (L)	0.6
Cooling	Air
Alternator	Brushless
Poles	2
Fuel tank capacity (L)	11
Consumption (L/h)	1.2 at 75% of the load / 1.6 at 100% of the load
Running time (h)	9.3 at 75% of the load / 7 at 100% of the load
Acoustic power	95 dB(A)
Acoustic pressure	67 dB(A) at 7 m
Length (mm)	623
Width (mm)	409
Height (mm)	500

---

Dry weight (Kg)	43
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Capacitor
Engine manufacturer	Honda

---