



PRAMAC ES8000 Single-Phase Gasoline Generator

Reference: PE612SH1000

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.4
Continuous power single phase (KW)	5.5
Maximum power single phase (KVA)	7.2
Continuous power single phase (KVA)	6
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A SCHUKO IP54 - 1 x 230V 32A 2P+T CEE IP44
Engine	Honda GX390 Recoil, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm ³)	389
Oil capacity (L)	1.1
Cooling	Air
Poles	2
Fuel tank capacity (L)	11
Consumption (L/h)	2.1 at 75% of the load / 2.9 at 100% of the load
Running time (h)	5.1 at 75% of the load / 3.8 at 100% of the load

Acoustic power	97 dB(A)
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	729
Width (mm)	500
Height (mm)	536
Dry weight (Kg)	73
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Capacitor
Engine manufacturer	Honda