

PRAMAC GBW35Y APERTO CON QUADRO COMANDO MANUALE (MCP)

Reference: SH260TYAQ00 /



Technical Sheet

| | |
|------------------------------------|---|
| Phase | Three phase |
| Maximum power three phase (KW) | 29.87 |
| Continuous power three phase (KW) | 28.38 |
| Maximum power three phase (KVA) | 37.34 |
| Continuous power three phase (KVA) | 35.48 |
| Fuel | Diesel |
| Frequency (Hz) | 50 |
| Voltage (V) | 400 |
| Sockets configuration | 1 x 400V 32A 3P+N+T CEE - 1 x 400V 16A 3P+N+T CEE - 2 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO |
| Engine | Yanmar 4TNV98-IGPGE, naturally aspirated |
| Emissions Regulations | Stage 3A |
| Speed governor | Mechanical |
| Starting system | Electric |
| Engine capacity (cm ³) | 3319 |
| Number cylinders | 4 |
| Cylinders' position | In line |
| Oil capacity (L) | 10.5 |
| Cooling | Water |
| Alternator | Mecc Alte ECP28-VL/4, brushless |
| Poles | 4 |
| Fuel tank capacity (L) | 51 |

| | |
|---------------------|--|
| Consumption (L/h) | 5.8 at 75% of the load / 7.7 at 100% of the load |
| Running time (h) | 8.8 at 75% of the load / 6.6 at 100% of the load |
| Length (mm) | 2000 |
| Width (mm) | 920 |
| Height (mm) | 1100 |
| Dry weight (Kg) | 558 |
| Inverter | No |
| AVR | Yes |
| Compound | No |
| Silenced | No |
| Super silenced | No |
| Product type | Generator |
| ATS Switch device | No ATS |
| Voltage regulator | AVR |
| Engine manufacturer | Yanmar |