



## SINCRO ET2 MBS Three Phase Synchronous AC Alternator 5.5 kVA Compound

Reference: ET2 MBS

Three phase brushes alternator - Compound.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 22.14 / cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

### Technical Sheet

|                         |                |
|-------------------------|----------------|
| Phase                   | Three phase    |
| Frequency (Hz)          | 50             |
| Voltage (V)             | 230 / 400      |
| Engine rpm (rpm)        | 3000           |
| Poles                   | 2              |
| Three-phase power (KW)  | 4.4            |
| Three-phase power (KVA) | 5.5            |
| Efficiency (%)          | 75             |
| Protection degree       | IP23           |
| Dry weight (Kg)         | 28.3           |
| Brushes                 | Yes            |
| Type of alternator      | Constant Speed |
| Voltage regulator       | Compound       |