



## SINCRO FT2 MFS Three Phase Synchronous AC Alternator 16 kVA Compound

Reference: FT2 MFS

Three phase brushes alternator - Compound.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

### Technical Sheet

Phase	Three phase
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Poles	2
Three-phase power (KW)	12.8
Three-phase power (KVA)	16
Efficiency (%)	84.5
Protection degree	IP23
Dry weight (Kg)	62
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	Digital AVR