



SINCRO ET2 LBR Three Phase Synchronous AC Alternator 10 kVA AVR

Reference: ET2 LBR

Three phase brushes alternator - AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 22.14 / cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

Technical Sheet

Phase	Three phase
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Poles	2
Three-phase power (KW)	8
Three-phase power (KVA)	10
Efficiency (%)	83
Protection degree	IP23
Dry weight (Kg)	38
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR