



FISCHER PANDA 15000i 400V Inverter Three-Phase Sea Generating Set 12 kW

Reference: 0013444 - P NO

FISCHER PANDA 15000i ThreePhase Marine Generator Supersilenced 15 KVA

Fischer Panda 15000i threephase marine generator designed to be compact, quiet and powerful with up to 30% weight and space savings! The Fischer Panda 15000i threephase is ideal for yacht owners who require low noise and vibration levels.

The Fischer Panda 15000i threephase features modern, innovative and environmentally friendly **inverter** technology.

The speed of the diesel engine is adjusted to suit the user's varying power requirements, while the output voltage from the inverter remains constant at all times. Variable speed control significantly reduces exhaust emissions and fuel consumption compared to a conventional fixed speed generator. The maximum engine speed of the Fischer three-phase is 2800 rpm. The electrical load is supplied with a constant output voltage of 230 V / 50 Hz or 120 V / 60 Hz via an inverter.

Technical specifications:

Phase type: Three-phase

Maximum three-phase power: 0-12 KW

Three-phase continuous power: 0-10.8 KW

Maximum three-phase power: 0-15 KVA

Three-phase continuous power: 0-13.5 KVA

Frequency: 50 Hz

Voltage: 230 V

Motor speed: 2200-2800 rpm

Displacement: 898

Cooling: Water

Sound pressure: 54 dB(A) at 7 m

Inverter

Length: 650 mm

Width: 465 mm

Height: 589 mm

Dry weight: 160 kg

The Fischer Panda 15000i features the renowned Fischer Panda sound insulation and water cooling.

The new Fischer Panda 15000i takes full advantage of modern diesel engines designed to run at lower speeds and meet current emission standards.

High performance

High starting performance for inductive loads such as air conditioning and underwater compressors and clean sine waveform with its precise voltage and frequency regulation ensures stable and efficient power supply for sensitive electronic devices.

- High starting capacity for air conditioners/compressors, which means there is no need to select large generators for starting currents.

- Highly efficient - maximum energy

- Pure sine wave ideal for sensitive electronics

- Reliable power supply (230V AC output)

New iControl2 Panel and Engine Controller

Designed by Fischer Panda for iSeries generators. The control panel allows you to operate the generator from the cab and view current status and technical data. The new panel is compact and can be installed on small dashboards.

Digital display

The new iControl2 is capable of recording and reading more data.

Automatic start function that allows the generator to start via an external electrical pulse. For example: a battery monitoring module could measure the battery level and give a signal to automatically start the Fischer Panda i-generator if it is below a preset value.

If you are looking for a marine generator like the Fischer Panda 15000i then you can browse the entire catalog of [marine generators](#).

Images and technical data are not binding. Please always consult the technical data sheet issued by the manufacturer. Manel Service accepts no liability for any changes made by the manufacturer.

Technical Sheet

Phase	Three phase
Maximum power three phase (KW)	12
Continuous power three phase (KW)	10.8
Maximum power three phase (KVA)	15
Continuous power three phase (KVA)	13.5
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	400
Engine	Kubota D902
Engine rpm (rpm)	2200 - 2800
Speed governor	Electronic
Starting system	Elettrico
Engine capacity (cm ³)	898
Number cylinders	3
Oil capacity (L)	3.7
Cooling	Water
Poles	2
Bore x stroke (mm)	72 x 73.6
Motor insulation class	H
Length (mm)	650
Width (mm)	465
Height (mm)	589
Dry weight (Kg)	160

Silenced	Yes
Super silenced	Yes
Product type	Generator
Voltage regulator	Inverter
Engine manufacturer	Kubota
