



LINZ E1E10M I Single-phase alternator 115V/230V 7 kVA 50 Hz AVR

Reference: E1E10M I 50 Hz

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

CHARACTERISTICS

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: AVR
- Application: PORTABLE

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	7
Continuous power single phase (KVA)	7
Frequency (Hz)	50
Voltage (V)	115 / 230
Engine rpm (rpm)	3000
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	7
Protection degree	IP21
Motor insulation class	H

Length (mm)	395
Width (mm)	195
Height (mm)	297
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	34
