



LINZ E1E10L L Single-phase alternator 110V/220V 9.75 kVA 60 Hz AVR

Reference: E1E10L L 60 Hz

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

CHARACTERISTICS

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: AVR
- Application: PORTABLE

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	9.75
Continuous power single phase (KVA)	9.75
Frequency (Hz)	60
Voltage (V)	110 / 220
Engine rpm (rpm)	3600
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	8.4
Protection degree	IP21
Motor insulation class	H

Length (mm)	395
Width (mm)	195
Height (mm)	297
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	37.5
