



## LINZ E1E11M B Single-phase alternator 115V/230V 10 kVA 50 Hz AVR

Reference: E1E11M B 50 Hz B3/B14

The **SPE** and **E1E** series consist of single-phase, 2-pole alternators with brushes and electronic AVR regulation.

### FEATURES

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Regulation: AVR
- Application: PORTABLE
- Available in 50 Hz and 60 Hz versions

### Technical Sheet

|                                     |                        |
|-------------------------------------|------------------------|
| Phase                               | Single phase           |
| Continuous power single phase (KW)  | 10                     |
| Continuous power single phase (KVA) | 10                     |
| Frequency (Hz)                      | 50 / 60                |
| Voltage (V)                         | 115 / 230              |
| Engine rpm (rpm)                    | 3000                   |
| Alternator                          | Synchronous, brushless |
| Poles                               | 2                      |
| Single-phase power (KVA)            | 10                     |
| Protection degree                   | IP21                   |
| Motor insulation class              | H                      |
| Length (mm)                         | 415                    |

---

|                    |                |
|--------------------|----------------|
| Width (mm)         | 230            |
| Height (mm)        | 215            |
| Brushes            | Yes            |
| Type of alternator | Constant Speed |
| Voltage regulator  | AVR            |
| Weight (Kg)        | 48             |

---