



LINZ E1E13S C Single-phase alternator 115V/230V 13 kVA 50 Hz AVR

Reference: E1E13S C 50 Hz SAE5 d8

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

CHARACTERISTICS

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: AVR
- Application: PORTABLE
product available in 50 Hz and 60 Hz

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	13
Continuous power single phase (KVA)	13
Frequency (Hz)	50 / 60
Voltage (V)	115 / 230
Engine rpm (rpm)	3000
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	13
Protection degree	IP21
Motor insulation class	H

Length (mm)	405
Width (mm)	270
Height (mm)	379
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	62
