



LINZ E1S10M H Three-phase alternator 230/400V 7 kVA 50 Hz Compound

Reference: E1S10M H 50 Hz J609a c 19

E1S/2 series are three-phase 2 poles alternators with brushes and compound regulation..

CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE
product available 50 Hz and 60 Hz

Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	5.6
Continuous power three phase (KVA)	7
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Single-phase power (KVA)	7
Protection degree	IP21

Motor insulation class	H
Length (mm)	294
Width (mm)	195
Height (mm)	295
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	Compound
Weight (Kg)	33.1