



## LINZ E1S11M B Three-phase alternator 230V/400V 13.5 kVA 50 Hz Compound

Reference: E1S11M B 50 Hz J609b

E1S/2 series are three-phase 2 poles alternators with brushes and compound regulation..

### CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE  
product available in 50 Hz and 60 Hz versions

### Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	10.8
Continuous power three phase (KVA)	13.5
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Single-phase power (KVA)	13.5
Protection degree	IP21

Motor insulation class	H
Length (mm)	415
Width (mm)	230
Height (mm)	325
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	Compound
Weight (Kg)	56.5