



LINZ E1X13S B/2 Three-phase alternator 230V/400V 10 kVA 50 Hz AVR

Reference: E1X13S B/2 50 Hz

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency

- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION

Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	8
Continuous power three phase (KVA)	10
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Single-phase power (KVA)	10
Protection degree	IP21

Motor insulation class	H
Length (mm)	465
Width (mm)	270
Height (mm)	379
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	62