



LINZ E1X13S B/2 Three-phase alternator 277V/480V 12.5 kVA 60 Hz AVR

Reference: E1X13S B/2 60 Hz

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION

Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	10
Continuous power three phase (KVA)	12.5
Frequency (Hz)	60
Voltage (V)	277 / 480
Engine rpm (rpm)	3600
Alternator	Synchronous
Poles	2
Single-phase power (KVA)	12.5
Protection degree	IP21

Motor insulation class	H
Length (mm)	465
Width (mm)	270
Height (mm)	379
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	62