



LINZ E1X13S C/2 Three-phase alternator 230V/400V 12.5 kVA 50 Hz AVR

Reference: E1X13S C/2 50 Hz J609b

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION
Product available in 50 Hz and 60 Hz versions

Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	10
Continuous power three phase (KVA)	12.5
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2

Three-phase power (KVA)	12.5
Protection degree	IP21
Motor insulation class	H
Length (mm)	465
Width (mm)	270
Height (mm)	379
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	69