



LINZ E1S10M H KE Three-phase alternator 230V/400V 5.5 kVA 50 Hz AVR + Compound

Reference: E1S10M H KE 50 Hz 60 Hz

E1S-KE series are three-phase 2 poles alternators with brushes and mixed regulation: compound and electronic (AVR).

CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND AND AVR
- Application: PORTABLE
product available in 50 Hz and 60 Hz versions

Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	4.4
Continuous power three phase (KVA)	5.5
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Single-phase power (KVA)	5.5
Protection degree	IP21

Motor insulation class	H
Length (mm)	294
Width (mm)	195
Height (mm)	295
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR+Compound
Weight (Kg)	33.1