



## LINZ E1S10M I KE Three-phase alternator 230V/400V 7 kVA 50 Hz AVR + Compound

Reference: E1S10M I KE 50 Hz J609a

**E1S-KE** series are three-phase 2 poles alternators with brushes and mixed regulation: compound and electronic (AVR).

### CHARACTERISTICS

- Possibility to feed any type of load
  - Compact and easy to assemble
  - High starting capacity
  - High efficiency
  
  - Type: Three-phase alternators
  - Poles: 2
  - Phases: Three-phase
  - Regulation: COMPOUND AND AVR
  - Application: PORTABLE
- Prodotto disponibile in versione 50 Hz e 60 Hz

### Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	5.6
Continuous power three phase (KVA)	7
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Single-phase power (KVA)	7
Protection degree	IP21

---

Motor insulation class	H
Length (mm)	294
Width (mm)	195
Height (mm)	295
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR+Compound
Weight (Kg)	37

---