



CAT CATERPILLAR P INV2000 INVERTER SILENT GENERATOR

Reference: INV2000

PORTABLE GENERATOR

- Equipped with dual USB input
- Extremely quiet and fuel efficient
- Has two access doors to make it easier to change oil, air filter or drain fuel
- Works with LED lighting for night use

Main features of CAT P INV2000:

- Single switch for operation
- Dual USB input for charging phones, laptops, tablets
- Sockets protected from the elements, dust, humidity, dirt in general, thanks to the rubber covers with snap fastening
- Control panel with LED lighting for night operation
- Intelligent engine control (ESC) saves fuel while generating energy
- Air filter access and fuel drainage door

The images are purely indicative.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2
Continuous power single phase (KW)	1.8
Maximum power single phase (KVA)	2.5
Continuous power single phase (KVA)	2.25
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 13A, 1 x 5V 2.1A USB, 1 x 5V 1.0A USB, 1 x 12V DC 8.3A
Engine	OHV

Engine rpm (rpm)	Variable
Starting system	Pull starter
Engine capacity (cm ³)	79.5
Fuel tank capacity (L)	4
Consumption (L/h)	0.68 at 50% of the load
Running time (h)	4 to 50% of load
Width (mm)	318
Height (mm)	460
Dry weight (Kg)	22.1
Silenced	Yes
ATS Switch device	No ATS
Voltage regulator	Inverter
Engine manufacturer	Caterpillar