



## LINZ E1S13S A/4 Three-phase alternator 4 poles 9.6 kVA 60 Hz Compound

Reference: E1S13S A/4 60 Hz

E1S13/4 series are three-phase 4 poles alternators with brushes and compound regulation.

### CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE

### Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	7.68
Continuous power three phase (KVA)	9.6
Frequency (Hz)	60
Voltage (V)	277 / 480
Engine rpm (rpm)	1800
Alternator	Synchronous
Poles	4
Three-phase power (KVA)	9.6

Protection degree	IP21
Motor insulation class	H
Length (mm)	403
Width (mm)	270
Height (mm)	379
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	Compound
Weight (Kg)	51