



LINZ E1S13M D/4 Three-phase alternator 4 poles 13 kVA 50 Hz Compound

Reference: E1S13M D/4 50 Hz

E1S13/4 series are three-phase 4 poles alternators with brushes and compound regulation.

CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE

Technical Sheet

| | |
|------------------------------------|-------------|
| Phase | Three phase |
| Continuous power three phase (KW) | 10.4 |
| Continuous power three phase (KVA) | 13 |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 / 400 |
| Engine rpm (rpm) | 1500 |
| Alternator | Synchronous |
| Poles | 4 |
| Three-phase power (KVA) | 13 |

| | |
|------------------------|----------------|
| Protection degree | IP21 |
| Motor insulation class | H |
| Length (mm) | 403 |
| Width (mm) | 270 |
| Height (mm) | 373 |
| Brushes | Yes |
| Type of alternator | Constant Speed |
| Voltage regulator | Compound |
| Weight (Kg) | 70.5 |