



## LINZ PRO35M F/4 Three-phase alternator 4 poles 670 kVA 50 Hz AVR

Reference: PRO35M F/4 50 Hz

The alternators of **PRO** series are three-phase brushless 4 poles with electronic regulation (AVR) with single-phase sensing (PRO18-PRO22) and three-phase sensing (PRO28-PRO35-PRO40).

### CHARACTERISTICS

- Compact and mechanically resistant
- Excellent wave form
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: AVR
- Application: INDUSTRIAL, COGENERATION

### Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	536
Continuous power three phase (KVA)	670
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	1500
Alternator	Synchronous
Poles	4
Three-phase power (KVA)	670

Protection degree	IP23
Motor insulation class	H
Length (mm)	1106
Width (mm)	732
Height (mm)	950
Brushes	No
PMG	Optional
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	1500.5